

Table 1: Properties of the Continuous-Time Fourier Series

Property	Periodic Signal	Fourier Series Coefficients
	$x(t) \left\{ \begin{array}{l} x(t) \\ y(t) \end{array} \right\}$ Periodic with period T and fundamental frequency $\omega_0 = 2\pi/T$	a_k b_k
Linearity	$Ax(t) + By(t)$	$Aa_k + Bb_k$
Time-Shifting	$x(t - t_0)$	$a_k e^{-jk\omega_0 t_0} = a_k e^{-jk(2\pi/T)t_0}$
Frequency-Shifting	$e^{jM\omega_0 t} = e^{jM(2\pi/T)t} x(t)$	a_{k-M}
Conjugation	$x^*(t)$	a_{-k}^*
Time Reversal	$x(-t)$	a_{-k}
Time Scaling	$x(\alpha t), \alpha > 0$ (periodic with period T/α)	a_k
Periodic Convolution	$\int_T x(\tau)y(t-\tau)d\tau$	$Ta_k b_k$
Multiplication	$x(t)y(t)$	$\sum_{l=-\infty}^{+\infty} a_l b_{k-l}$
Differentiation	$\frac{dx(t)}{dt}$	$jk\omega_0 a_k = jk \frac{2\pi}{T} a_k$
Integration	$\int_{-\infty}^t x(t)dt$ (finite-valued and periodic only if $a_0 = 0$)	$\left(\frac{1}{jk\omega_0} \right) a_k = \left(\frac{1}{jk(2\pi/T)} \right) a_k$ $\left\{ \begin{array}{l} \Re\{a_k\} = \Re\{a_{-k}\} \\ \Im\{a_k\} = -\Im\{a_{-k}\} \\ a_k = a_{-k} \\ \not\propto a_k = -\not\propto a_{-k} \end{array} \right.$ a_k real and even
Conjugate Symmetry for Real Signals	$x(t)$ real	
Real and Even Signals	$x(t)$ real and even	
Real and Odd Signals	$x(t)$ real and odd	a_k purely imaginary and odd
Even-Odd Decomposition of Real Signals	$\left\{ \begin{array}{ll} x_e(t) = \mathcal{E}v\{x(t)\} & [x(t) \text{ real}] \\ x_o(t) = \mathcal{O}d\{x(t)\} & [x(t) \text{ real}] \end{array} \right.$	$\Re\{a_k\}$ $j\Im\{a_k\}$
Parseval's Relation for Periodic Signals		
	$\frac{1}{T} \int_T x(t) ^2 dt = \sum_{k=-\infty}^{+\infty} a_k ^2$	

Table 2: Properties of the Discrete-Time Fourier Series

Property	Periodic signal	Fourier series coefficients
	$x[n] \left\{ \begin{array}{l} x[n] \\ y[n] \end{array} \right\}$ Periodic with period N and fundamental frequency $\omega_0 = 2\pi/N$	a_k b_k
Linearity	$Ax[n] + By[n]$	$Aa_k + Bb_k$
Time shift	$x[n - n_0]$	$a_k e^{-jk(2\pi/N)n_0}$
Frequency Shift	$e^{jM(2\pi/N)n} x[n]$	a_{k-M}
Conjugation	$x^*[n]$	a_{-k}^*
Time Reversal	$x[-n]$	a_{-k}
Time Scaling	$x_{(m)}[n] = \begin{cases} x[n/m] & \text{if } n \text{ is a multiple of } m \\ 0 & \text{if } n \text{ is not a multiple of } m \end{cases}$ (periodic with period mN)	$\frac{1}{m} a_k$ (viewed as periodic with period mN)
Periodic Convolution	$\sum_{r=\langle N\rangle} x[r]y[n-r]$	$N a_k b_k$
Multiplication	$x[n]y[n]$	$\sum_{l=\langle N\rangle} a_l b_{k-l}$
First Difference	$x[n] - x[n-1]$	$(1 - e^{-jk(2\pi/N)})a_k$
Running Sum	$\sum_{k=-\infty}^n x[k]$ (finite-valued and periodic only if $a_0 = 0$)	$\left(\frac{1}{(1 - e^{-jk(2\pi/N)})} \right) a_k$
Conjugate Symmetry for Real Signals	$x[n]$ real	$\left\{ \begin{array}{l} a_k = a_{-k}^* \\ \Re\{a_k\} = \Re\{a_{-k}\} \\ \Im\{a_k\} = -\Im\{a_{-k}\} \\ a_k = a_{-k} \\ \not\propto a_k = -\not\propto a_{-k} \end{array} \right.$ a_k real and even
Real and Even Signals	$x[n]$ real and even	
Real and Odd Signals	$x[n]$ real and odd	
Even-Odd Decomposition of Real Signals	$\left\{ \begin{array}{ll} x_e[n] = \mathcal{E}v\{x[n]\} & [x[n] \text{ real}] \\ x_o[n] = \mathcal{O}d\{x[n]\} & [x[n] \text{ real}] \end{array} \right.$	a_k purely imaginary and odd $\Re\{a_k\}$ $j\Im\{a_k\}$
Parseval's Relation for Periodic Signals		
	$\frac{1}{N} \sum_{n=\langle N\rangle} x[n] ^2 = \sum_{k=\langle N\rangle} a_k ^2$	

Table 3: Properties of the Continuous-Time Fourier Transform

$$x(t) = \frac{1}{2\pi} \int_{-\infty}^{\infty} X(j\omega) e^{j\omega t} d\omega$$

$$X(j\omega) = \int_{-\infty}^{\infty} x(t) e^{-j\omega t} dt$$

Property	Aperiodic Signal	Fourier transform
	$x(t)$	$X(j\omega)$
	$y(t)$	$Y(j\omega)$
Linearity	$ax(t) + by(t)$	$aX(j\omega) + bY(j\omega)$
Time-shifting	$x(t - t_0)$	$e^{-j\omega_0 t} X(j\omega)$
Frequency-shifting	$e^{j\omega_0 t} x(t)$	$X(j(\omega - \omega_0))$
Conjugation	$x^*(t)$	$X^*(-j\omega)$
Time-Reversal	$x(-t)$	$X(-j\omega)$
Time- and Frequency-Scaling	$x(at)$	$\frac{1}{ a } X\left(\frac{j\omega}{a}\right)$
Convolution	$x(t) * y(t)$	$X(j\omega)Y(j\omega)$
Multiplication	$x(t)y(t)$	$\frac{1}{2\pi} X(j\omega) * Y(j\omega)$
Differentiation in Time	$\frac{d}{dt} x(t)$	$j\omega X(j\omega)$
Integration	$\int_{-\infty}^t x(t) dt$	$\frac{1}{j\omega} X(j\omega) + \pi X(0)\delta(\omega)$
Differentiation in Frequency	$tx(t)$	$j \frac{d}{d\omega} X(j\omega)$
Conjugate Symmetry for Real Signals	$x(t)$ real	$\begin{cases} X(j\omega) = X^*(-j\omega) \\ \Re\{X(j\omega)\} = \Re\{X(-j\omega)\} \\ \Im\{X(j\omega)\} = -\Im\{X(-j\omega)\} \\ X(j\omega) = X(-j\omega) \\ \Im X(j\omega) = -\Im X(-j\omega) \end{cases}$
Symmetry for Real and Even Signals	$x(t)$ real and even	$X(j\omega)$ real and even
Symmetry for Real and Odd Signals	$x(t)$ real and odd	$X(j\omega)$ purely imaginary and odd
Even-Odd Decomposition for Real Signals	$x_e(t) = \mathcal{E}v\{x(t)\}$ [$x(t)$ real] $x_o(t) = \mathcal{O}d\{x(t)\}$ [$x(t)$ real]	$\Re\{X(j\omega)\}$ $j\Im\{X(j\omega)\}$

Parseval's Relation for Aperiodic Signals

$$\int_{-\infty}^{+\infty} |x(t)|^2 dt = \frac{1}{2\pi} \int_{-\infty}^{+\infty} |X(j\omega)|^2 d\omega$$

Table 4: Basic Continuous-Time Fourier Transform Pairs

Signal	Fourier transform	Fourier series coefficients (if periodic)
$\sum_{k=-\infty}^{+\infty} a_k e^{jk\omega_0 t}$	$2\pi \sum_{k=-\infty}^{+\infty} a_k \delta(\omega - k\omega_0)$	a_k
$e^{j\omega_0 t}$	$2\pi\delta(\omega - \omega_0)$	$a_1 = 1$ $a_k = 0, \text{ otherwise}$
$\cos \omega_0 t$	$\pi[\delta(\omega - \omega_0) + \delta(\omega + \omega_0)]$	$a_1 = a_{-1} = \frac{1}{2}$ $a_k = 0, \text{ otherwise}$
$\sin \omega_0 t$	$\frac{\pi}{j} [\delta(\omega - \omega_0) - \delta(\omega + \omega_0)]$	$a_1 = -a_{-1} = \frac{1}{2j}$ $a_k = 0, \text{ otherwise}$
$x(t) = 1$	$2\pi\delta(\omega)$	$a_0 = 1, a_k = 0, k \neq 0$ (this is the Fourier series representation for any choice of $T > 0$)
Periodic square wave $x(t) = \begin{cases} 1, & t < T_1 \\ 0, & T_1 < t \leq \frac{T}{2} \end{cases}$ and $x(t+T) = x(t)$	$\sum_{k=-\infty}^{+\infty} \frac{2 \sin k\omega_0 T_1}{k} \delta(\omega - k\omega_0)$	$\frac{\omega_0 T_1}{\pi} \operatorname{sinc}\left(\frac{k\omega_0 T_1}{\pi}\right) = \frac{\sin k\omega_0 T_1}{k\pi}$
$\sum_{n=-\infty}^{+\infty} \delta(t - nT)$	$\frac{2\pi}{T} \sum_{k=-\infty}^{+\infty} \delta\left(\omega - \frac{2\pi k}{T}\right)$	$a_k = \frac{1}{T}$ for all k
$x(t) \begin{cases} 1, & t < T_1 \\ 0, & t > T_1 \end{cases}$	$\frac{2 \sin \omega T_1}{\omega}$	—
$\frac{\sin Wt}{\pi t}$	$X(j\omega) = \begin{cases} 1, & \omega < W \\ 0, & \omega > W \end{cases}$	—
$\delta(t)$	1	—
$u(t)$	$\frac{1}{j\omega} + \pi\delta(\omega)$	—
$\delta(t - t_0)$	$e^{-j\omega_0 t_0}$	—
$e^{-at} u(t), \Re\{a\} > 0$	$\frac{1}{a + j\omega}$	—
$te^{-at} u(t), \Re\{a\} > 0$	$\frac{1}{(a + j\omega)^2}$	—
$\frac{t^{n-1}}{(n-1)!} e^{-at} u(t), \Re\{a\} > 0$	$\frac{1}{(a + j\omega)^n}$	—

Table 5: Properties of the Discrete-Time Fourier Transform

$$x[n] = \frac{1}{2\pi} \int_{2\pi} X(e^{j\omega}) e^{j\omega n} d\omega$$

$$X(e^{j\omega}) = \sum_{n=-\infty}^{+\infty} x[n] e^{-j\omega n}$$

Property	Aperiodic Signal	Fourier transform
Linearity	$x[n]$ $y[n]$	$X(e^{j\omega})$ Periodic with $Y(e^{j\omega})$ period 2π
Time-Shifting	$ax[n] + by[n]$	$aX(e^{j\omega}) + bY(e^{j\omega})$
Frequency-Shifting	$x[n - n_0]$	$e^{-j\omega n_0} X(e^{j\omega})$
Conjugation	$e^{j\omega_0 n} x[n]$	$X(e^{j(\omega-\omega_0)})$
Time Reversal	$x^*[n]$	$X^*(e^{-j\omega})$
Time Expansions	$x[-n]$	$X(e^{-j\omega})$
Convolution	$x[n] * y[n]$	$X(e^{j\omega}) Y(e^{j\omega})$
Multiplication	$x[n]y[n]$	$\frac{1}{2\pi} \int_{2\pi} X(e^{j\theta}) Y(e^{j(\omega-\theta)}) d\theta$
Differencing in Time	$x[n] - x[n - 1]$	$(1 - e^{-j\omega}) X(e^{j\omega})$
Accumulation	$\sum_n x[k]$	$\frac{1}{1 - e^{-j\omega}} X(e^{j\omega})$ $+ \pi X(e^{j0}) \sum_{k=-\infty}^{+\infty} \delta(\omega - 2\pi k)$
Differentiation in Frequency	$nx[n]$	$j \frac{dX(e^{j\omega})}{d\omega}$
Conjugate Symmetry for Real Signals	$x[n]$ real	$\begin{cases} X(e^{j\omega}) = X^*(e^{-j\omega}) \\ \Re\{X(e^{j\omega})\} = \Re\{X(e^{-j\omega})\} \\ \Im\{X(e^{j\omega})\} = -\Im\{X(e^{-j\omega})\} \\ X(e^{j\omega}) = X(e^{-j\omega}) \\ \not\propto X(e^{j\omega}) = -\not\propto X(e^{-j\omega}) \end{cases}$
Symmetry for Real, Even Signals	$x[n]$ real and even	$X(e^{j\omega})$ real and even
Symmetry for Real, Odd Signals	$x[n]$ real and odd	$X(e^{j\omega})$ purely imaginary and odd
Even-odd Decomposition of Real Signals	$x_e[n] = \mathcal{E}v\{x[n]\}$ $[x[n]$ real] $x_o[n] = \mathcal{O}d\{x[n]\}$ $[x[n]$ real]	$\begin{aligned} &\Re\{X(e^{j\omega})\} \\ &j\Im\{X(e^{j\omega})\} \end{aligned}$

Parseval's Relation for Aperiodic Signals

$$\sum_{n=-\infty}^{+\infty} |x[n]|^2 = \frac{1}{2\pi} \int_{2\pi} |X(e^{j\omega})|^2 d\omega$$

Table 6: Basic Discrete-Time Fourier Transform Pairs

Signal	Fourier transform	Fourier series coefficients (if periodic)
$\sum_{k=(N)} a_k e^{jk(2\pi/N)n}$	$2\pi \sum_{k=-\infty}^{+\infty} a_k \delta\left(\omega - \frac{2\pi k}{N}\right)$	a_k
$e^{j\omega_0 n}$	$2\pi \sum_{l=-\infty}^{+\infty} \delta(\omega - \omega_0 - 2\pi l)$	(a) $\omega_0 = \frac{2\pi n}{N}$ $a_k = \begin{cases} 1, & k = m, m \pm N, m \pm 2N, \dots \\ 0, & \text{otherwise} \end{cases}$ (b) $\frac{\omega_0}{2\pi}$ irrational \Rightarrow The signal is aperiodic
$\cos \omega_0 n$	$\pi \sum_{l=-\infty}^{+\infty} \{\delta(\omega - \omega_0 - 2\pi l) + \delta(\omega + \omega_0 - 2\pi l)\}$	(a) $\omega_0 = \frac{2\pi n}{N}$ $a_k = \begin{cases} \frac{1}{2}, & k = \pm m, \pm m \pm N, \pm m \pm 2N, \dots \\ 0, & \text{otherwise} \end{cases}$ (b) $\frac{\omega_0}{2\pi}$ irrational \Rightarrow The signal is aperiodic
$\sin \omega_0 n$	$\frac{\pi}{j} \sum_{l=-\infty}^{+\infty} \{\delta(\omega - \omega_0 - 2\pi l) - \delta(\omega + \omega_0 - 2\pi l)\}$	(a) $\omega_0 = \frac{2\pi r}{N}$ $a_k = \begin{cases} \frac{1}{2j}, & k = r, r \pm N, r \pm 2N, \dots \\ -\frac{1}{2j}, & k = -r, -r \pm N, -r \pm 2N, \dots \\ 0, & \text{otherwise} \end{cases}$ (b) $\frac{\omega_0}{2\pi}$ irrational \Rightarrow The signal is aperiodic
$x[n] = 1$	$2\pi \sum_{l=-\infty}^{+\infty} \delta(\omega - 2\pi l)$	$a_k = \begin{cases} 1, & k = 0, \pm N, \pm 2N, \dots \\ 0, & \text{otherwise} \end{cases}$
Periodic square wave		
$x[n] = \begin{cases} 1, & n \leq N_1 \\ 0, & N_1 < n \leq N/2 \end{cases}$ and $x[n+N] = x[n]$	$2\pi \sum_{k=-\infty}^{+\infty} a_k \delta\left(\omega - \frac{2\pi k}{N}\right)$	$a_k = \frac{\sin[(2\pi k/N)(N_1 + \frac{1}{2})]}{N \sin[2\pi k/2N]}$, $k \neq 0, \pm N, \pm 2N, \dots$ $a_k = \frac{1}{2N_1 + 1}$, $k = 0, \pm N, \pm 2N, \dots$
$\sum_{k=-\infty}^{+\infty} \delta[n - kN]$	$\frac{2\pi}{N} \sum_{k=-\infty}^{+\infty} \delta\left(\omega - \frac{2\pi k}{N}\right)$	$a_k = \frac{1}{N}$ for all k
$a^n u[n]$, $ a < 1$	$\frac{1}{1 - ae^{-j\omega}}$	—
$x[n] \begin{cases} 1, & n \leq N_1 \\ 0, & n > N_1 \end{cases}$	$\frac{\sin[\omega(N_1 + \frac{1}{2})]}{\sin(\omega/2)}$	—
$\frac{\sin W n}{\pi n} = \frac{W}{\pi} \operatorname{sinc}\left(\frac{W n}{\pi}\right)$, $0 < W < \pi$	$X(\omega) = \begin{cases} 1, & 0 \leq \omega \leq W \\ 0, & W < \omega \leq \pi \end{cases}$ $X(\omega)$ periodic with period 2π	—
$\delta[n]$	1	—
$u[n]$	$\frac{1}{1 - e^{-j\omega}} + \sum_{k=-\infty}^{+\infty} \pi \delta(\omega - 2\pi k)$	—
$\delta[n - n_0]$	$e^{-j\omega n_0}$	—
$(n+1)a^n u[n]$, $ a < 1$	$\frac{1}{(1 - ae^{-j\omega})^2}$	—
$\frac{(n+r-1)!}{n!(r-1)!} a^n u[n]$, $ a < 1$	$\frac{1}{(1 - ae^{-j\omega})^r}$	—

Table 9: Properties of the z -Transform

Property	Sequence	Transform	ROC
	$x[n]$	$X(z)$	R
	$x_1[n]$	$X_1(z)$	R_1
	$x_2[n]$	$X_2(z)$	R_2
Linearity	$ax_1[n] + bx_2[n]$	$aX_1(z) + bX_2(z)$	At least the intersection of R_1 and R_2
Time shifting	$x[n - n_0]$	$z^{-n_0}X(z)$	R except for the possible addition or deletion of the origin
Scaling in the z -Domain	$e^{j\omega_0 n}x[n]$ $z_0^n x[n]$ $a^n x[n]$	$X(e^{-j\omega_0}z)$ $X\left(\frac{z}{z_0}\right)$ $X(a^{-1}z)$	R $z_0 R$ Scaled version of R (i.e., $ a R$ is the set of points $\{ a z\}$ for z in R)
Time reversal	$x[-n]$	$X(z^{-1})$	Inverted R (i.e., R^{-1} = the set of points z^{-1} where z is in R)
Time expansion	$x_{(k)}[n] = \begin{cases} x[r], & n = rk \\ 0, & n \neq rk \end{cases}$ for some integer r	$X(z^k)$	$R^{1/k}$ (i.e., the set of points $z^{1/k}$ where z is in R)
Conjugation	$x^*[n]$	$X^*(z^*)$	R
Convolution	$x_1[n] * x_2[n]$	$X_1(z)X_2(z)$	At least the intersection of R_1 and R_2
First difference	$x[n] - x[n - 1]$	$(1 - z^{-1})X(z)$	At least the intersection of R and $ z > 0$
Accumulation	$\sum_{k=-\infty}^n x[k]$	$\frac{1}{1-z^{-1}}X(z)$	At least the intersection of R and $ z > 1$
Differentiation in the z -Domain	$nx[n]$	$-z \frac{dX(z)}{dz}$	R
Initial Value Theorem If $x[n] = 0$ for $n < 0$, then $x[0] = \lim_{z \rightarrow \infty} X(z)$			

Table 10: Some Common z -Transform Pairs

Signal	Transform	ROC
1. $\delta[n]$	1	All z
2. $u[n]$	$\frac{1}{1-z^{-1}}$	$ z > 1$
3. $-u[-n - 1]$	$\frac{1}{1-z^{-1}}$	$ z < 1$
4. $\delta[n - m]$	z^{-m}	All z except 0 (if $m > 0$) or ∞ (if $m < 0$)
5. $\alpha^n u[n]$	$\frac{1}{1-\alpha z^{-1}}$	$ z > \alpha $
6. $-\alpha^n u[-n - 1]$	$\frac{1}{1-\alpha z^{-1}}$	$ z < \alpha $
7. $n\alpha^n u[n]$	$\frac{\alpha z^{-1}}{(1-\alpha z^{-1})^2}$	$ z > \alpha $
8. $-n\alpha^n u[-n - 1]$	$\frac{\alpha z^{-1}}{(1-\alpha z^{-1})^2}$	$ z < \alpha $
9. $[\cos \omega_0 n]u[n]$	$\frac{1 - [\cos \omega_0]z^{-1}}{1 - [2 \cos \omega_0]z^{-1} + z^{-2}}$	$ z > 1$
10. $[\sin \omega_0 n]u[n]$	$\frac{[\sin \omega_0]z^{-1}}{1 - [2 \cos \omega_0]z^{-1} + z^{-2}}$	$ z > 1$
11. $[r^n \cos \omega_0 n]u[n]$	$\frac{1 - [r \cos \omega_0]z^{-1}}{1 - [2r \cos \omega_0]z^{-1} + r^2 z^{-2}}$	$ z > r$
12. $[r^n \sin \omega_0 n]u[n]$	$\frac{[r \sin \omega_0]z^{-1}}{1 - [2r \cos \omega_0]z^{-1} + r^2 z^{-2}}$	$ z > r$